75 Ohm Interconnect



Designed as a flexible solution for network signal management, ADC's Digital Monitor Module (DMM) system provides a centralized coaxial termination and interconnection point between network elements (NE). The DMM system allows a permanent, dedicated connection between two NEs while providing dual, nonintrusive test access points for bidirectional monitoring of the network signal. Ensuring unsurpassed quality, this interconnect solution features cable management designed to increase reliability, maintain signal flow, and allow easy cable identification. To enhance network flexibility, the DMM system allows modules to be installed in a chassis as network requirements increase.

#### Features:

- · Provides bidirectional, nonintrusive signal testing
- Supports E1 (2.048 Mbps), E3 (34.368 Mbps), or STM-1 (155.52 Mbps) signal rate applications
- · Modular design allows for capital investment to coincide with revenue growth
- Mounts in standard 600 mm bays
- · Quality cable management and circuit identification markings






75 Ohm Interconnect

### **Application**

The DMM system is used primarily in co-location environments, DDF locations, and customer premises as a connection point between NEs. Each NE is semipermanently cabled to IN/OUT connectors in either the front or rear of each module. The digital signal is accessed through the two MON OUT connectors on the front of each module for testing and monitoring. These dual monitor ports allow access to both directions of the circuit from a single location. This saves valuable technician time when the other side of the termination is located far away, in another room, or is inaccessible.



2



75 Ohm Interconnect

### Configurations

The DMM system is available in several chassis and rack configurations to create a customized interconnect solution. Each module is ordered separately and may be installed in any DMM chassis or rack configuration as the network expands, allowing capital investment to coincide with revenue growth.

#### **Modules**

Multiple connector interface types and locations are available to complement existing network designs. Individual modules allow chassis to easily match existing NE circuit counts.

### **Standard Configuration**

Up to 12, 24-position chassis are designed to mount in a standard 600 mm rack for a total of 288 circuits. Cable management bars, trays, and labeling are provided on each chassis.

### **High-Density Configuration**

This uniquely designed dual chassis features two separate compartments, each accommodating up to

eight modules mounted horizontally. The two compact compartments are mounted side-by-side in a specially designed dual-column 600 mm rack. This high-density configuration allows a total of 352 circuits in one rack. Cable management bars and four vertical cabling ducts ensure proper routing for high-density cabling.

#### **Wall-Mount Box**

This six-position enclosure serves as an interconnect demarcation point between network providers and customers. Separate locks on each door secure connections from unwanted access.

3



75 Ohm Interconnect

### Modules

### **Features:**

- Front, dual monitor ports on all module styles
- BNC or 1.6/5.6 connectors provide true 75 Ohm characteristic impedance
- All module styles are compatable with any DMM 600 mm chassis style

#### Ordering Information Description **IN/OUT Connector Locations** Catalog Number **BNC** DMM-BBNCMF **BNC** Front and Rear DMM-BBNCF **BNC Bulkhead** DMM-BNCBLK Front and Rear 1.6/5.6 DMM-1656MF Rear 1.6/5.6 Front and Rear DMM-1656F 1.6/5.6 Bulkhead Front and Rear DMM-1656BLK DMM-BLANK Blank None



DMM-BBNCMF Rear and Front View



DMM-BBNCF Rear and Front View



DMM-BNCBLK Rear and Front View



DMM-1656MF Rear and Front View



DMM-1656F Rear and Front View



DMM-1656BLK Rear and Front View



75 Ohm Interconnect

### Standard Configuration

#### **Features:**


- 288 total circuits in fully loaded bay
- Cable bars and front cable trays, with cable tie-downs, reduce cable congestion and simplify maintenance
- Circuit designation labels above connectors and on cable tray ensure proper cable routing and identification
- Bay equipped with cable troughs, vertical wiring ducts, and equipment cable tie-down bars
- · Zone 4 earthquake-rated rack with EIA mounting spacing



D3C-0024T Front View

5

Ordering Information		
Description	Dimensions (HxWxD)	Ordering Number
Unloaded Chassis accomodates up to 24 modules	113 x 482.6 x 228.6 mm (4.4" x 19" x 9")	D3C-0024T
600 mm Skeleton Bay accomodates up to 12 modules	2200 x 600 x 475 mm (86.6" x 23.6" x 18.7")	IBR-D3C001





75 Ohm Interconnect

### **High-Density Configuration**

#### **Features:**


- Improved circuit density by 20%; 352 circuits in fully loaded bay
- Cable bars reduce cable congestion and simplify maintenance
- · Circuit designation label door ensures proper cable routing and identification
- Bay equipped with four vertical cabling channels, cable troughs, and equipment cable tie-down bars for high density cable management
- · Zone 4 earthquake-rated equal-flange rack with EIA mounting spacing




D3C-0016HD Front View

### Ordering Information

Description	Dimensions (HxWxD)	Ordering Number
Unloaded Pair of Dual Chassis accomodates up to 16 modules in two, eight-position chassis	88 x 236 x 165 mm (3.5" x 9.3" x 6.5")	D3C-0016HD
600 mm Dual Skeleton Bay accomodates up to 11 dual chassis	2200 x 600 x 250 mm (86.7" x 23.6" x 23.6")	IBC-D3C001







+1-952-938-8080

1-800-366-3891



75 Ohm Interconnect

### Wall-Mount Box

### **Features:**

- Used as a demarcation point when NEs are supplied by the service provider and by the customer premises
- Seperate locks on each door secure connections from unwanted access



D3C-WBOX06 Front View

Ordering Information		
Description	Dimensions (HxWxD)	Ordering Number
Unloaded Wall-Mount Box accomodates up to 6 modules	267 x 203 x 114 mm (10.5" x 8" x 4.5")	D3C-WBOX06

Note: Modules are ordered seperately

### Specifications

ELECTRICAL Insertion Loss

Insertion Loss

Better than -.5 dB, 100 KHz to 100 MHz
Better than -.8 dB, 100 MHz to 300 MHz

Return Loss:

Better than -20 dB, 100 KHz to 300 MHz

Monitor Loading Effect:

< .4 dB change in insertion loss to 300 MHz

**Monitor Level:** 21.5  $\pm$  1.5 dB, 100 KHz to 300 MHz

Isolation:< -55 dB at 22.368 MHz</td>Cross Talk:< -55 dB at 22.368 MHz</td>Phase Delay< 4 nanoseconds to 300 MHz</td>Pulse Template:Conform to CCITT Recomm. G.703

**MECHANICAL** 

**Retention Force:** 7 lbs. minimum **Retention Torque:** 4" per lbs. minimum

ENVIRONMENTAL

**Thermal Shock:** -40°C to +60°C operating

-55°C to +85°C non-operating

Moisture Resistance: 0% to 95%





#### Web Site: www.adc.com

From North America, Call Toll Free: 1-800-366-3891 • Outside of North America: +1-952-938-8080 Fax: +1-952-917-3237 • For a listing of ADC's global sales office locations, please refer to our web site.

ADC Telecommunications, Inc., P.O. Box 1101, Minneapolis, Minnesota USA 55440-1101 Specifications published here are current as of the date of publication of this document. Because we are continuously improving our products, ADC reserves the right to change specifications without prior notice. At any time, you may verify product specifications by contacting our headquarters office in Minneapolis. ADC Telecommunications, Inc. views its patent portfolio as an important corporate asset and vigorously enforces its patents. Products orfeatures contained herein may be covered by one or more U.S. or foreign patents. An Equal Opportunity Employer

103978AE 12/06 Revision © 2002, 2006 ADC Telecommunications, Inc. All Rights Reserved